



## BASIC 80



<b>Certification</b>	<b>UNI EN12352 L2H</b>
Input voltage	<b>12/24 VDC</b>
Colour	● ● ●
Max. power consumption	<b>4.1 W</b>
Dimensions	<b>Ø 88 x 21.5 mm</b>


Flashing	<b>Power cons. @12V</b>	
Flash LED (10%)	<b>0.82 Ah</b>	/day
Tri Flash (5%+5%+5%)	<b>1.23 Ah</b>	/day
Single (50%)	<b>4.1 Ah</b>	/day
Steady	<b>8.2 Ah</b>	/day

FL (FlashLed) 10%

Basic 80 and Basic 102 are LED warning lights for fixed or temporary use especially appropriate when reduced dimension is needed.

They are available only with external control and they are suitable for all the application where there is a need to warn, inform or guide road users.

Some examples of applications:



Adapter for Basic 80

## BASIC 102



<b>Certification</b>	<b>UNI EN12352 L2H</b>
Input voltage	<b>12 VDC</b>
Colour	● ● ● ●
Max. power consumption	<b>3.8 W</b>
Dimensions	<b>Ø 139 x 19 mm</b>

Flashing	<b>Power cons. @12V</b>	
Flash LED (10%)	<b>0.8 Ah</b>	/day
Tri Flash (5%+5%+5%)	<b>1.2 Ah</b>	/day
Single (50%)	<b>4.0 Ah</b>	/day
Steady	<b>8.0 Ah</b>	/day



Adattaper for Basic 102